DATASHEET - PKZM0-XDM12



Kit, +component adapter, for DOL starter for DILM7-M15



(Norway)

PKZM0-XDM12 283149 log XTPAXTPCB

4365079



Delivery program

Product range	Accessories
Accessories	Wiring set
	For DOL Starter
For use with	PKZM0, PKE + DILM7 PKZM0, PKE + DILM9 PKZM0, PKE + DILM12 PKZM0, PKE + DILM15 DS7-34SX004 DS7-34SX007 DS7-34SX009 DS7-34SX012
Equipment supplied:	Mechanical connection element for PKZM0 and contactor + main current wiring between PKZM0 and contactor with tool-less plug connection + cable routing
Instructions	Use as auxiliary contact DILA-XHIT Cannot be combined with NHI-E…PKZ0-C. Ue ≦ 415 V

Design verification as per IEC/EN 61439

I _n		
l _n		
	A	15.5
P _{vid}	W	0.5
P _{vid}	W	1.5
P _{vs}	W	0
P _{diss}	W	0
	°C	-25
	°C	55
		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Meets the product standard's requirements.
t		Meets the product standard's requirements.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Meets the product standard's requirements.
		Does not apply, since the entire switchgear needs to be evaluated.
		Does not apply, since the entire switchgear needs to be evaluated.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		Is the panel builder's responsibility.
		The panel builder is responsible for the temperature rise calculation. Eaton will provide heat dissipation data for the devices.
	P _{vid} P _{vid} P _{vs}	P _{vid} W P _{vid} W P _{vs} W P _{diss} W C C C

10.11 Short-circuit rating	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.12 Electromagnetic compatibility	Is the panel builder's responsibility. The specifications for the switchgear must be observed.
10.13 Mechanical function	The device meets the requirements, provided the information in the instruction leaflet (IL) is observed.

Technical data ETIM 7.0

Low-voltage industrial components (EG000017) / Wiring set for power circuit breaker (EC002050)					
Electric engineering, automation, process control engineering / Low-voltage switch technology / Circuit breaker (LV < 1 kV) / Wiring set for circuit breaker (ecl@ss10.0.1-27-37-04-24 [ACN957011])					
Suitable for number of poles	3				
Model	Direct circuit				
Approvals					
Product Standards	UL 508; CSA-C22.2 No. 14; IEC60947-4-1; CE marking				
UL File No.	E36332				
UL Category Control No.	NLRV				
CSA File No.	165628				
CSA Class No.	3211-05				
North America Certification	UL listed, CSA certified				
Specially designed for North America	No				

Assets (links)

Declaration of CE Conformity 00002771 Instruction Leaflets IL034017ZU2018_06

Additional product information (links)

IL034017ZU Wiring kits direct-on-line starter

•	
IL034017ZU Wiring kits direct-on-line starter	ftp://ftp.moeller.net/DOCUMENTATION/AWA_INSTRUCTIONS/IL034017ZU2018_06.pdf
Motor starters and "Special Purpose Ratings" for the North American market	http://www.eaton.eu/ecm/groups/public/@pub/@europe/@electrical/documents/content/pct_3258146.pdf
Busbar Component Adapters for modern Industrial control panels	http://www.moeller.net/binary/ver_techpapers/ver960en.pdf